

MEASUREMENT OF THE ELECTRIC CURRENT IN A KPC-SCALE JET

P.P. KRONBERG¹

Institute of Geophysics and Planetary Physics, Los Alamos National Laboratory T006, Los Alamos NM 87545, and Department of Physics, University of Toronto, 60 St George St., Toronto ON M5S 1A7

R.V.E. LOVELACE²

Departments of Astronomy and Applied and Engineering Physics, Cornell University, Ithaca, NY 14853-6801

G. LAPENTA³

Centre for Plasma Astrophysics, Departement Wiskunde, Katholieke Universiteit Leuven, Belgium (EU)

S.A. COLGATE⁴

Los Alamos National Laboratory, Los Alamos NM 87545

Draft version May 21, 2013

ABSTRACT

We present radio emission, polarization, and Faraday rotation maps of the radio jet of the galaxy 3C303. From this data we derive the magnetoplasma and electrodynamic parameters of this 50 kpc long jet. For one component of this jet we obtain for the first time a direct determination of a *galactic-scale* electric current ($\sim 10^{18}$ A), and its direction – *positive* away from the AGN. Our analysis strongly supports a model where the jet energy flow is mainly *electromagnetic*.

Subject headings: AGN, Jet current, Poynting flux

1. INTRODUCTION

The outward transport of electromagnetic energy and angular momentum in jets from accretion disks (with little mass outflow) in the form of a collimated, magnetically-dominated (or ‘Poynting-flux jet’) was first proposed by Lovelace (1976) and Blandford (1976) and subsequently studied in many papers (Benford 1978; Lovelace, Wang, & Sulkanen 1987; Lynden-Bell 1996; Li, et al. 2001; Lovelace, et al. 2002; 2003; Nakamura et al. 2008). The model has a collimated current outflow (or inflow) I_z along the spine of the jet of cylindrical radius r_J (normal to the disk plane). An equal but opposite “return current” flow inward (or outward) at much larger distances from the jet axis must occur, so that the net current outflow from the source is zero. Because the jet current and its return have opposite signs they repel, as a result of their magnetic interaction mediated by the toroidal magnetic field B_ϕ . This repulsion between the jet and its return current has been clearly demonstrated and discussed in MHD simulations (Ustyugova et al. 2000, 2006; Nakamura et al. 2008). The toroidal magnetic field is responsible for collimating the jet. At the same time the toroidal field gives an outward radial force on the annular return current, pushing it away from the jet axis.

Rotation measure gradients observed in a number of active galactic nuclei jets provide evidence for electric current flow along the jet axis (Gabuzda, Murray, & Cronin 2004; Zavala & Taylor 2005). Here, we present evidence for a large current flow on a 10^4 times as large a scale. The 3C303 radio source at $z = 0.141$ (Figure 1) has a one-sided prominent jet with regular repeating knot structures in both radio and X-ray bands (Kronberg, 1976, 1986; Lapenta & Kronberg 2005 (LK05); Kataoka et al. 2003). It

resides in a relatively sparsely populated intergalactic environment, and at a high galactic latitude $(l, b) = (+90^\circ.5, +57^\circ.5)$. Being away from a galaxy cluster, it is well-suited to an analysis of Faraday rotation measures (RM) within the jet and lobes, since competing Faraday RM variations from an immediate cluster environment and the Galactic foreground are small. In this situation, we applied new improved determinations of background radio source RM’s around an extragalactic radio source (Kronberg & Newton-McGee 2011) to make one of the most precise estimates of the “RM zero-level” for an extragalactic source. This is a requirement for verifying the true *loci* of magnetic field sign reversals, and hence for estimating patterns of electric current in BH-powered extragalactic systems.

The above combination of radio and X-ray images plus background source RM’s permits the jet’s physical parameters, including its current, to be analysed in isolation. 3C303’s radiating knots are large, a few thousand times larger in volume than those in the well-studied nearby M87 radio galaxy. The laterally unresolved “spine” of its jet is surrounded by a “cocoon” of relativistic, hence radio-visible, gas mixed with thermal plasma which has both a low plasma - β (ratio of plasma pressure to magnetic pressure) and a highly ordered magnetic field (Fig.1). The jet’s regular structure, combined with the appearance of a transverse, magnetically coherent, western lobe complex suggests it as a clear laboratory of jet disruption. Model simulations by LK05 applied MHD soliton-like solutions of the Grad-Shafranov equation to the radio and X-ray radio images of the regular knot structure of the 3C303 jet. Their models successfully computed jet stability times and constrained its plasma parameters. The latter form a basis for this paper, independent of the model details.

kronberg@lanl.gov

lovelace@astro.cornell.edu

giovanni.lapenta@kuleuven.nl

colgate@lanl.gov

It is also apparent that the jet continues beyond the disruption point in Figure 1(a), and terminates in a bow shock-like extremity to the west. To the east, large polarized loop is also seen, as well as a possibly related “counter hotspot” that aligns with the western jet. We do not attempt an interpretation of either of these latter two features.

We describe a rare opportunity to resolve the absolute Faraday rotation (RM) variation *transverse* to the jet axis in one of the knots (E3 in Figure 1(b)). Combined with the full plasma diagnostics, and a determination of the RM zero-level from surrounding sources this provides, for the first time a direct estimate of both the magnitude and sign of a jet’s *net electric current* on kiloparsec scales in intergalactic space.

2. THE JET STRUCTURE AND KNOTS OF 3C303

The partial resolution of the knots in the VLA images at 1.4 and 4.9 GHz permits estimates of the relativistic gas energy and magnetic field strength within each, kpc-scale synchrotron radiating knot (cocoon). These were estimated by LK05 from the best fit gaussian dimensions of the three prominent knots in the images in Figure 1.

In our study of 3C303’s kpc scale jet, we distinguish the spine, which is laterally unresolved and appears to carry the jet power, from the “knots”, which are partially resolved cocoons around the unresolved “spine”. In this article the term “knot” will refer to the resolved and extended radiating cocoon. It contains a mix of magnetized thermal and relativistic plasma. There is no significant growth in the knot widths away from the AGN, which puts an *upper* limit on the opening angle of this jet of 0.7° .

The first stage in measuring the jet current is to calculate the approximate magnetic field strengths in the knots using standard equipartition arguments. Note that the knots’ equipartition magnetic field strength estimates depend only weakly on the volume filling ϕ , as $\phi^{-2/7}$, and on the upper cutoff frequency of the photon spectrum of the jet’s emission. The latter extends to 10^{17} Hz (Kataoka *et al.*, 2003), and its reduction by, say $\times 100$, would reduce the (redshift-corrected) total energy content in the knots by only 30%. At lower particle energies the uncertain extrapolation of the knots’ relativistic particle energy spectrum, corresponding to (unobserved) very low radio frequencies, could affect our estimate of $|\mathbf{B}|$ by a modest factor less than unity. In the following analysis we estimate a field strength in the core volumes of 3C303’s jet knots, $B_{\text{knot}} \sim 0.5$ milligauss, measured with a $0.35''$ beam and allowing for some out-of-plane component.

At the $0.3''$ resolution of the 4.9GHz VLA image, the projected line-of-sight, emission-weighted magnetic field orientation within each knot is parallel to the jet axis (Fig. 1). The percentage polarizations of knots E₁, E₂, and E₃ are $\sim 27\%$, 21% , and 26% , respectively, and the knots are elongated in the jet direction with aspect ratios of $\sim 6.5 : 1$, $2.5 : 1$, and $2.8 : 1$ respectively. Curiously, Figure 1 shows at both frequencies that the polarization structure at the leading edge of *each* knot contains orientation changes. These appear to reflect the actual magnetic field structure, and not a Faraday rotation effect.

3. THE FARADAY ROTATION, THERMAL ELECTRON DENSITY AND ALFVÉN SPEED

Figure 2 shows the 2-D RM variation within the brighter parts of the 3C303 system at a common $1.5''$ resolution at 1.4 and 4.9 GHz. Values range between $+5$ and $+25$ rad m^{-2} over a maximum extent of $\sim 50''$, which includes 3C303’s extended western lobe. The 3rd jet knot, E3, is resolved just enough to show an RM gradient, which is transverse to the jet axis. The varying RM in knot E3 confirms the presence of some thermal plasma in the cocoon. The differential RM around knot E3 is ~ 10 radians m^{-2} .

Having measured a differential RM over the knot, its dimension, and the approximate magnetic field strength, we can estimate the non-relativistic plasma density within the knot via the following equation.

$$\text{RM} = 7.3 \times 10^5 \left(\frac{n_e}{\text{cm}^{-3}} \right) \left(\frac{B_{\parallel}}{\text{mG}} \right) \left(\frac{x}{900\text{pc}} \right) \frac{\text{rad}}{\text{m}^2},$$

$$\approx 10 \frac{\text{rad}}{\text{m}^2},$$

where x is the line-of-sight distance through the knot. Inserting B_{\parallel} and x gives $n_e \sim 1.4 \times 10^{-5} \text{cm}^{-3}$.

This simultaneously gives an estimate of the knot-internal Alfvén speed of this low- β plasma cocoon. We find that V_A is somewhat less than the speed of light. Using the non-relativistic formula,

$$V_A = 2.2 \times 10^9 \left(\frac{B}{\text{mG}} \right) \left(\frac{10^{-5} \text{cm}^{-3}}{n_e} \right)^{1/2} \text{cm s}^{-1}.$$

These numbers argue for an electromagnetically dominated jet, as concluded by LK05.

An independent estimate of n_e can be made from the observed polarization *degree* in the knots. On the reasonable assumption that the very regular field geometry in knot E3 results from a low pitch angle helical geometry, knot-internal Faraday dispersion is limited by the high observed degree of polarization $\simeq 25\%$ at 5 GHz. This implies a back-to-front, knot-internal differential Faraday rotation at 5GHz of $\lesssim 30^\circ$, consistent with the knot’s RM observed above. This confirms the above n_e estimate and gives us confidence in the local n_e scaling that is required to estimate the jet current - which we discuss next.

4. ESTIMATE OF THE ELECTRICAL CURRENT IN THE 3C303 JET

The final step in relating (∇RM) to a current is to calibrate the RM zero level. This was done by averaging the discrete source RM’s at neighbouring (l,b) to 3C303 from a recent accurate RM dataset (Kronberg & Newton-McGee 2011). The resulting RM zero-level correction of $-18 \pm 4^\circ$ has been applied to the RM scale of Figure 2. With this zero-level correction, we find that the RM in knot E3 changes sign *on* the jet axis, within the limit of our uncertainties. Furthermore, its gradient (∇RM) is found to be perpendicular to the axis of knot E3 and the jet. This corresponds to the expected RM behavior around an electric current flowing along the axis (z) of the jet.

The reversal of RM sign just on the jet axis matches the signature of a current-carrying “wire”, where we are measuring an azimuthal component of magnetic field strength

at an approximate mean y distance on opposite sides of the synchrotron radiating cocoon surrounding the unresolved spine of the jet. The inferred current, I_z , is an average within the cocoon's radiating volume, over which we measure the transverse $\nabla(\text{RM})$ of $\sim 10 \text{ rad m}^{-2}/\text{kpc}$. The result is

$$I_z \sim 7.5 \times 10^{17} \left(\frac{B_\phi}{10^{-3}\text{G}} \right) \left(\frac{y}{0.5\text{kpc}} \right) \text{ A}, \quad (1)$$

where B_ϕ is the toroidal component of magnetic field strength at a distance y (assumed = x) in the sky plane from the jet (z) axis, scaled to 0.5 mG. The current is measured over a z - distance of $\sim 2.1h_{75}^{-1} \text{ kpc}$, the projected z - length of knot E3. The positive sign of the gradient $\nabla(\text{RM}) = \Delta(\text{RM}_y)/\Delta y$ indicates that a net current of $\sim 3.8 \times 10^{17}$ ampères, for $B_{\text{equi}}=0.5 \text{ mG}$, is directed *away* from the galaxy nucleus. That is, along the jet axis there is a net flow of negative charge toward the AGN core within knot E3.

Our result above depends on an estimate on the likelihood that the knot lies in the plane of the sky, and that $B_{\text{equi}} \simeq B_{\text{azim}}$ in the jet knot. If the B has a low pitch angle helical form about the z axis, consistent with an average projected field direction in the z direction observed, the net current would be reduced by a geometrical factor of a few. This would scale $\langle \mathbf{i} \rangle$ closer to 10^{17} A .

5. DISCUSSION AND IMPLICATIONS

A Poynting-flux jet can be modeled as a coaxial transmission line running in the z -direction with the electric potential drop across it ΔV . This is equal to the potential drop across the disk from its inner- to outer radius (Lovelace 1976; Lovelace and Ruchti 1983). A typical value is $\Delta V \sim 10^{19}\text{V}(B_{bh}/10^3\text{G})(M_{bh}/10^8M_\odot)$, where B_{bh} is the poloidal magnetic field strength near the black hole and M_{bh} is its mass (Lovelace 1976). The current flow in the "transmission line" is $I_z = \Delta V/Z$, where the impedance is

$$Z \sim c^{-1}(\text{cgs}) = \frac{1}{4\pi} \left(\frac{\mu_0}{\epsilon_0} \right)^{1/2} (\text{MKS}) = 30\Omega, \quad (2)$$

(Lovelace 1976). The value of Z depends of course on the distribution of the poloidal magnetic field threading the accretion disk. The power transported by the jet is simply $L_{\text{jet}} = I_z^2 Z$.

We can now apply these ideas to the 3C303 system. The total photon luminosity L_{rad} integrated from 10^8 Hz to 10^{17} Hz is about $3.7 \times 10^{41} \text{ erg s}^{-1}$ or $3.7 \times 10^{34} \text{ W}$. The radiated power is expected to be significantly less than the jet power, because the jet power goes into a combination of $p dV$ work on the ambient medium and to energizing ions and electrons in the outer radiating lobes. Thus, we let $L_{\text{rad}} = \epsilon L_{\text{jet}}$, where $\epsilon < 1$ is an efficiency factor. Substituting the observed values of L_{rad} and I_z we find

$$\epsilon = \frac{L_{\text{rad}}}{I_z^2 Z} \approx \quad (3)$$

$$0.0087 \left(\frac{P}{3.7 \times 10^{34}\text{W}} \right) \left(\frac{3.8 \times 10^{17}\text{A}}{I_z} \right)^2 \left(\frac{30\Omega}{Z} \right).$$

Hence ϵ is $\sim 1\%$, safely less than unity, and the model of Poynting flux transport of jet energy in 3C 303's black hole/accretion disk system appears to be self-consistent. The system evidently needs to have a "transducer" that converts the Poynting energy flux into high energy particles which then produce synchrotron radiation. It is important that the efficiency factor of this conversion is not much different from the gravitational to relativistic magneto-plasma energy conversion efficiency in outer radio lobes (Kronberg, Dufton, Li, & Colgate, 2001). This number varies from $\sim 1\%$ for medium size radio lobes as for 3C303, to $\sim 20\%$ in giant radio sources.

ACKNOWLEDGEMENTS

We thank Rick Perley, Robert Reid, Justin Linford and Greg Taylor for help and advice with the re-calibrated images, and Hui Li for discussion of current flow in jets. Support is acknowledged from a Natural Sciences and Engineering Research of Canada Discovery Grant (PPK) and from NSF and NASA (RVEL).

REFERENCES

- Benford, G. 1978, MNRAS, 183, 29
 Blandford, R.D. 1976, MNRAS, 176, 465
 Gabuzda, D.C., Murray, E., & Cronin, P. 2004, MNRAS, 351, L89
 Kataoka, J., Edwards, P., Georganopoulos, M., Takahara, F., & Wagner, S. 2003, A&A, 399, 91
 Kronberg, P.P. 1976, ApJ, 203, L47
 Kronberg, P.P. 1986, Can. J. Phys., 64, 449
 Kronberg, P.P. & Newton-McGee, K. J. 2011, Publ. Astr. Soc. Australia, in press
 Kronberg, P.P., Dufton, Q. W., Li, H., & Colgate, S. A. 2001 ApJ, 560, 178
 Lapenta, G., & Kronberg, P.P. 2005 ApJ, 625, 37 (LK05)
 Li, H., Lovelace, R.V.E., Finn, J.M., & Colgate, S.A. 2002, ApJ, 561, 915
 Lovelace, R.V.E. 1976, Nature, 262, 649
 Lovelace, R.V.E., Wang, J.C.L., & Sulkanen, M.E. 1987, ApJ, 315, 504
 Lovelace, R. V. E., Li, H., Koldoba, A. V., Ustyugova, G. V., & Romanova, M. M. 2002, ApJ, 572, 445
 Lynden-Bell, D. 1996, MNRAS, 279, 389
 Nakamura, M., Tregillis, I.L., Li, H., & Li, S. 2008, ApJ, 686, 843
 Newton-McGee, K. J. & Kronberg, P.P. 2011 (accepted)
 Ustyugova, G. V., Lovelace, R. V. E., Romanova, M. M., Li, H., & Colgate, S. A. 2000, ApJ, 541, L21
 Ustyugova, G. V., Koldoba, A. V., Romanova, M. M., & Lovelace, R. V. E. 2006, ApJ, 646, 304
 Zavala, R.T., & Taylor, G.B. 2005, ApJ, 626, L73




FIG. 1.— (a) 1.4 GHz, $1.5''$ resolution VLA image of the entire 3C303 system showing an apparent counter-jet knot, the highly polarized western lobe, and a continuation of the jet to its final western stopping point. Linear polarization lines are scaled such that $1''$ equivalent length = 2.5 mJy/beam. I -contours are shown at -0.5, 0.5, 1, 1.5, 2, 3, 6, 12, 24, 50, 100, and 150 mJy/beam. (b) A 4.9GHz VLA image of the 3C303 jet at $0.35''$ resolution showing the 3 prominent, elongated and equally spaced knots E1, E2, and E3 to the right of the stronger, variable milliarcsec-size galaxy nucleus source.




FIG. 2.— Faraday rotation image of the 3C303 radio source at a resolution of $1.5''$. The RM zero level has been corrected by $18 \pm 4^\circ$ (see text).